

MIST INTERFACE

Intempco Controls - MIST Ver. 1.4

Configuration
Communication Port:
Units:

MIST

MIST - Configuration
Serial Number : 011016001
Range : -200.00 oC to 600 oC

Message:

MIST 16 - Calibration Ver.1.4

Operation Range
From : oC => 4.00 mA Preset Range:
To : oC => 20.00 mA

1 Point Calibration
Set RTD to a known temperature and press "+" and/or "-" to adjust to the corresponding 4-20mA output
For a Temperature of oC , theoretical output should be mA

2 Points Calibration (Optional)
1: First Point : oC
2: Second Point : oC
3: Calibrate :

Sensor Failure Settings
Sensor Failure:
☒ Up (24.0 mA) ☐ Down (2.5 mA)

Factory Use Only
S/N:

Actual Reading
NO MIST mA →
Adjustment: